

Model	Step Angle	Rated Voltage	Current/Phase Amp	Resistance/Phase $\Omega$	Inductance/Phase MH	Holding Torque kgcm	Rotor Inertia gcm	Weight kg	Nos. of Leads	Drawings
16H-20-04-4A	1.8	7.2	0.4	18	12	0.65	11gcm	0.12	4	<a href="#">Click Here</a>
16H-34-04-4A	1.8	12	0.4	30	3.2	1.8	20gcm	0.18	4	<a href="#">Click Here</a>
17H-48-10-6A	1.8	4	1	3.3	2.8	3.4	54	0.28	6	<a href="#">Click Here</a>
17H-48-10-4A	1.8	10.2	1	10.2	11	4.2	260	0.35	4	<a href="#">Click Here</a>
23H-56-10-4A	1.8	9	1	1.8	30	7.2	280	0.65	4	<a href="#">Click Here</a>
23H-56-10-6B	1.8	6.6	1	6.6	10	7.2	280	0.68	6	<a href="#">Click Here</a>
23H-64-28-4A	1.8	2.3	2.8	0.83	2.2	10	350	0.65	4	<a href="#">Click Here</a>
23H-76-28-4B	1.8	3.08	2.8	1.13	3.8	20	480	1	4	<a href="#">Click Here</a>
23H-76-28-4A	1.8	3.08	2.8	1.13	3.8	20	480	1	4	<a href="#">Click Here</a>
23H-100-30-4A	1.8	4.2	3	1.4	5.5	25	800	1.6	4	<a href="#">Click Here</a>
34H-78-30-4A	1.8	4.45	3	1.5	13.6	34	1400	1.7	4	<a href="#">Click Here</a>
34H-100-40-4A	1.8	3.8	4	0.95	7.5	48	2000	3.4	4	<a href="#">Click Here</a>
34H-126-50-4A	1.8	3.8	5	0.76	9	68	1600	4.5	4	<a href="#">Click Here</a>
34H-155-50-4A	1.8	4.08	5	0.68	9	87	4000	5.6	4	<a href="#">Click Here</a>
42H-125-60-4A	1.8	6.6	6	1.1	18	150	11000	8	4	<a href="#">Click Here</a>
42H-150-60-4A	1.8	5.1	6	0.9	15.9	220	11000	9.3	4	<a href="#">Click Here</a>
42H-201-80-4A	1.8	5.36	6	0.67	12	300	16200	11.7	4	<a href="#">Click Here</a>